

6 DIGIT MICROPROCESS COUNTER,72x72mm

**MODEL
MC726**



FEATURES

- Accepts input rates up to 10KHz
- Accept input rates 50 or 10000 CPS can be modified
- Four counting modes Up,Down,Up/Down, quadrature can be modified
- Quadrature sensing up to 4 times resolution
- Input scaling multiplied 0.00001 to 9.99999 can be modified
- Pre-warm counter function (two alarm output) can be modified
- Simulation pushwheel digit switches,easy to operate
- Count inhibit function(GATE control)
- Three alarm function (optional)



1:MODEL:MC726-

NO	Input Type	NO	Input Rates	NO	Alarm Output	NO	Aux.Power
A	Pulse (TTL) (5V)	1	50 pulse/sec	0	None	A	AC/DC18-60V
B	Pulse (NPN) (12V)	2	10000 pulse/sec	1	One	B	AC/DC90-260V
C	Pulse (PNP) (12V)	1:Contact input 2:Non-contact input		2	Two	Less 4VA for AC/DC input	
O	SPECIFIED			3	Two (AL2=Pre-warm)		
				4	Three		

3:OUTSIDE DIMENSION AND CONNECTION DIAGRAM

2:SPECIFICATION

- Count input type : Jump-pin selectable current sourcing(NPN) or current sinking (PNP)
- Count input trigger levels : HI bias (CMOS) ($V_{IH}=7.5V$, $V_{IL}=5.5V$)
LO bias (TTL) ($V_{IH}=3.7V$, $V_{IL}=2.0V$)
- Max.count rates : <10KHz (up,down,up/down mode)
<5KHz (quadrature mode)
- Output hold time : 0.1 to 99.9 second adjustable
- Output reset type : Manual(N) or automatic (R or C) can be modified
- Relay contact output : AC 250V-5A, DC 30V-7A
- Readout (compare)rang : -199999 to 999999
- Display : Red high efficiency LEDs high 9.2mm (.36")
- Parameter setting : Touch switches
- Sensor power supply : 12VDC +/-3%(<60mA)
- Memory mode : Non-volatile E² PROM memory
- Dielectric strength : 2KVac/1 min. (input/output/power)
1600Vdc (input/output)
- Operating condition : 0-50 (20 to 90% RH non-condensed)
- Storage condition : 0-70 (20 to 90% RH non-condensed)
- CE EMC Certification : EN 55022:1998/A1:2000 Class A
EN 61000-3-2:2000
EN 61000-3-3:1995/A1:2001
EN 55024:1998/A1:2001



PANEL CUT-OUT

